

# MODEL P1261P



**PORTABLE TWO CIRCUIT OUTDOOR  
TIMER WITH GROUND FAULT PROTECTION.  
TOTAL LOAD NOT TO EXCEED: 15A. RESISTIVE, 1800W  
(15A.) TUNGSTEN, 1 HP (15 FLA, 90 LRA) -120 VOLT 60 HZ.  
Suitable for Pool/Spa Equipment Control**

## IMPORTANT

This portable timer is designed for **CONTROLLING** the connected equipment only. Unplug timer before servicing the unit or the equipment it controls. ***THIS DEVICE IS NOT TO BE USED AS A POWER DISCONNECT!*** For maximum protection against electrical shock hazard, perform test procedure on GFCI at least once a month. If used to control pool/spa equipment install at least 5 feet from inside edge of pool/spa.

## GFCI TEST PROCEDURE

The GFCI should be checked every month to make sure it is operating properly. It is recommended that a permanent record of the monthly safety check is maintained.


1. Push TEST button. RESET button should pop out from inner surface. This should result in power being OFF at the outlets. Verify by plugging test lamp into either outlet. Be sure the timer is in the ON position.
2. If the GFCI tests okay, restore power by pushing the RESET button back in. THE RESET BUTTON MUST BE PUSHED FIRMLY AND FULLY INTO PLACE UNTIL IT LOCKS AND REMAINS DEPRESSED AFTER PRESSURE HAS BEEN REMOVED.

**DANGER** IF RESET BUTTON DOES **NOT** POP OUT, IF TEST LAMP **REMAINS LIT** WHEN RESET BUTTON DOES POP OUT, OR IF GFCI **FAILS TO RESET PROPERLY, DO NOT USE TIMER! CONTACT A QUALIFIED SERVICE TECHNICIAN!**

## TIMER - OPERATING INSTRUCTIONS

1. Insert ON (GREEN) and OFF (RED) trippers into dial at desired ON and OFF times.
2. Turn dial clockwise and align arrow with Time-of-Day (AM or PM) in window.

## FOR TEMPORARY MANUAL OPERATION

Rotate MANUAL knob counter-clockwise  to desired ON or OFF position. Timer will follow next automatic operation.

**INTERMATIC INCORPORATED**

SPRING GROVE, ILLINOIS 60081-9698