SIEMENS

Data sheet

3RA2125-1FA24-0BB4

	Fuseless motor starter Direct start 600VAC Size S0 3.5-5A 24V DC screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) 1NO+1NC (contactor)		
product brand name	SIRIUS		
product designation	non-fused motor starter 3RA2		
design of the product	direct starter		
manufacturer's article number			
 of the supplied contactor 	3RT2024-1BB40		
 of the supplied circuit-breakers 	3RV2011-1FA15		
of the supplied link module	3RA2921-1BA00		
General technical data			
size of the circuit-breaker	S00		
size of load feeder	S0		
product extension auxiliary switch	Yes		
insulation voltage with degree of pollution 3 at AC rated value	690 V		
degree of pollution	3		
surge voltage resistance rated value	6 kV		
shock resistance according to IEC 60068-2-27	6g / 11 ms		
mechanical service life (operating cycles) of contactor typical	10 000 000		
type of assignment	2		
Ambient conditions	2		
ambient temperature			
during operation	-20 +60 °C		
during storage	-50 +80 °C		
during storage during transport	-55 +80 °C		
Main circuit	-55 100 0		
militaria de mala de mala de mala de mala de maria			
number of poles for main current circuit	3		
design of the switching contact	electromechanical		
design of the switching contact adjustable current response value current of the current- dependent overload release			
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 3.5 5 A		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 3.5 5 A 690 V		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 3.5 5 A 690 V 690 V		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 3.5 5 A 690 V		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 3.5 5 A 690 V 690 V		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W 24 V 5.9 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W 24 V 5.9 W		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class design of the overload release	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W 24 V 5.9 W CLASS 10 thermal (bimetallic)		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC • rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class design of the overload release response value current of instantaneous short-circuit trip unit UL/CSA ratings	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W 24 V 5.9 W CLASS 10 thermal (bimetallic)		
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 3.5 5 A 690 V 690 V 50 60 Hz 3.6 A 1 500 W 2 200 W 24 V 5.9 W CLASS 10 thermal (bimetallic)		

at 600 V rated value	4.55	4	
yielded mechanical performance [hp]			
 for single-phase AC motor 			
— at 110/120 V rated value	0.17	пр	
— at 230 V rated value	0.5 h)	
• for 3-phase AC motor			
— at 200/208 V rated value	1 hp		
— at 220/230 V rated value	1 hp		
— at 460/480 V rated value	3 hp		
— at 575/600 V rated value	3 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	magn	etic	
conditional short-circuit current (Iq)			
at 400 V according to IEC 60947-4-1 rated value	153 0	00 A	
at 500 V according to IEC 60947-4-1 rated value	100 0		
Installation/ mounting/ dimensions	100 0	0071	
mounting position	vertic	al	
fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug		
height		193.1 mm	
width	45 mi		
depth	107 mm		
required spacing	107 11		
• for grounded parts			
— forwards	10 mm		
— backwards	0 mm		
— upwards	30 mm		
— at the side	9 mm		
— downwards	9 mm 10 mm		
	10 1111	11	
• for live parts	40		
— forwards	10 mm		
— backwards	0 mm		
— upwards	30 mm		
— downwards	10 mm		
— at the side	9 mm		
Connections/ Terminals			
type of electrical connection for main current circuit		screw-type terminals	
type of connectable conductor cross-sections for main contacts stranded	1 10 mm², 2x (2.5 6 mm²)		
connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²		
Safety related data			
B10 value with high demand rate according to SN 31920	1 000 000		
proportion of dangerous failures with high demand rate according to SN 31920	73 %	73 %	
protection class IP on the front according to IEC 60529	IP20		
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front		
Certificates/ approvals			
		For use in hazard-	

Confirmation











Test Certificates

Marine / Shipping

Special Test Certificate

Type Test Certificates/Test Report









Marine / Shipping other Railway Dangerous Good







<u>Confirmation</u> <u>Vibration and Shock</u> <u>Transport Information</u>

Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-1FA24-0BB4

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-1FA24-0BB4

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-1FA24-0BB4

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2125-1FA24-0BB4&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-1FA24-0BB4/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-1FA24-0BB4&objecttype=14&gridview=view1

last modified:	12/15/2020 🖸
	12/15/2020