Product specifications

# Eaton AN16SN0BB

## Catalog Number: AN16SN0BB

Eaton Freedom NEMA motor control starter, NEMA Freedom Series Non-Reversing Reset Overload Relay Starter, 75 hp at 208V, 100 hp at 240V, 200 hp at 480,600V maximum horsepower, 240V/60 Hz or 220V/50 Hz coil voltage, 270A, Three-pole, Size 5



## General specifications

**Product Name**
Eaton Freedom NEMA motor control starter

**Catalog Number**
AN16SN0BB

**UPC**
782113058986

**Product Length/Depth**
7.75 in

**Product Height**
7.22 in

**Product Width**
12 in

**Product Weight**
25 lb

**Warranty**
Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.

**Certifications**
CSA Certified
UL Listed

**Catalog Notes**
Heater Packs must be purchased separately

Powering Business Worldwide

## defaultTaxonomyAttributeLabel

### Special features

Starter w/C306 bi-metal OLR

### Phase

Three-phase

### Amperage Rating

270A

### Size

5

### Horsepower

75 hp at 208 V, 100 hp at 240 V, 200 hp at 480/600 V

### Mounting

Horizontal

## Resources

### Catalogs

Eaton's Volume 5—Motor Control and Protection

### Drawings

AN16SN0_B AutoCAD 2D Footprint (mm)

AN16SN0_B 2D PDF

AN16SN0_B 3D Model Xchange

AN16SN0_B 3D Inventor

AN16SN0_B AutoCAD 2D Footprint

AN16SN0_B 2D Drawing Xchange

### Specifications and datasheets

Quick Selector - NEMA Contactors

Eaton Specification Sheet - AN16SN0BB

### Warranty guides

Selling Policy 25-000 - Distribution and Control Products and Services

Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Eaton.com/socialmedia