

# Product data sheet

Specifications

**SQUARE D**



NEMA Motor Starter, Type S, replacement coil, 208VAC 60Hz, NEMA Size 00, 0 and 1 starters and 8903SM lighting

3104140048

Product availability: Stock - Normally stocked in distribution facility

## Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SA (series A)/SB/SC contactor Class 8536 type SA (series A)/SB/SC starter Class 8903 type SM lighting contactor

## Complementary

NEMA size	0 00 1
[Ue] rated operational voltage	208 V AC 60 Hz
inrush power in VA	245 VA
Average consumption	27 VA
Height	2.2 in (54.7 mm)
Width	3.2 in (81.5 mm)
Depth	1.9 in (48.3 mm)

## Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901107378
Returnability	Yes
Country of origin	MX

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.100 in (5.334 cm)
Package 1 Width	2.800 in (7.112 cm)
Package 1 Length	3.300 in (8.382 cm)
Package weight(Lbs)	7.040 oz (199.580 g)

## Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

### Use Longer



#### Lifetime extension

Repair

No

### Use Again



#### Repack and remanufacture

Take-back

No