

Product data sheet

Specifications

SQUARE D



NEMA Motor Starter, Type S, replacement coil, 110/120VAC 50/60Hz, NEMA Size 00, 0 and 1 starters and 8903SM lighting

3104140042

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SA (series A)/SB/SC contactor Class 8536 type SA (series A)/SB/SC starter Class 8903 type SM lighting contactor

Complementary

NEMA size	1 00 0
[Ue] rated operational voltage	120 V AC 60 Hz 110 V AC 50 Hz
inrush power in VA	245 VA 232 VA
Average consumption	27 VA 26 VA
Height	2.2 in (54.7 mm)
Width	3.2 in (81.5 mm)
Depth	1.9 in (48.3 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901229124
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.200 in (5.588 cm)
Package 1 Width	2.900 in (7.366 cm)
Package 1 Length	3.500 in (8.890 cm)
Package weight(Lbs)	22.300 lb(US) (10.115 kg)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **Yes**

Use Longer



Lifetime extension

Repair **No**

Use Again



Repack and remanufacture

Circularity Profile **No need of specific recycling operations**

Take-back **No**